

## Input module INPUT 8 DC/DC

Module for up to 8 digital inputs for programming the outgoing circuits



The EM 8K and EM 8F modules are now used instead of the EM 8I24 VDC module - with the same functionality.

An additional installation can also be easily implemented in existing systems.

A green LED per input indicates its status.

3 yellow LEDs inform about the status of the data bus.

**Funktionalität** Via external potential-free contacts, each of the eight inputs can be assigned to one or more circuits of the emergency lighting system. Each of the eight inputs can be assigned to one or more circuits of the emergency lighting system via external potential-free contacts. Each of the eight inputs can be assigned to one or more circuits of the emergency lighting system via external potential-free contacts. Translated with [www.DeepL.com/Translator](http://www.DeepL.com/Translator) (free version)

**Status display** Both the status of the data bus and the status of each individual input is indicated by LEDs.

LED lights up green. The external contact is closed

LED does not light up. The external contact is open

**Installation** The input module can be installed both in the central unit and in the sub-distributors of the emergency lighting.

### Technical data

|                     |                 |
|---------------------|-----------------|
| Inputs:             | 8 x 24 Vdc      |
| Supply voltage:     | 24 VDC          |
| Dimensions (WxHxD): | 53 x 90 x 58 mm |